

230V ~ 24V DC Transformer with Push Dim

24VDC transformer, where the dimmer is built-in and managed by Push DIM.

24VDC transformer, where the dimmer is built-in and managed by Push. The transformer has a precise dimming, from 0.1% to 100%, and since it is PWM dimming, it does not change the color nor the quality of the light (CRI).

The transformer has built in protection against short-circuit, overheating, overconsumption and over-voltage. See the datasheets for more facts and details about connecting the transformer.

Buy online at:

www.matronics.eu/504380



75W

SKU 504379

Input voltage: 100-240VAC

Power: >0.99

Output voltage: 24VDC

Consumption: 75W

Current: 3.12A

Temperature: - 30°C ~ 60°C

Weight: 490

Dimensions: 34 x 204 x 62mm



150W

SKU 504380

Input voltage: 100-240VAC

Power: >0.99

Output voltage: 24VDC

Consumption: 150W

Current: 6.25A

Temperature: - 30°C ~ 60°C

Weight: 580

Dimensions: 36 x 270 x 55mm