



230V PIR motion sensor for mounting in the ceiling - 5A

A nice motion-sensor for walls and ceilings. Easy to be built-in, just as a spot lamp. A timer and Lux-settings make it very flexible.



A nice motion-sensor for walls and ceilings. Easy to be build in, just as a spot lamp. A timer and Lux-settings make it very flexible.

Perfect for hallways and other rooms, where it is common only for a short period of time to be people there. With the Lux-sensitivity it is also possible to set it up only to turn on the light, if the rooms are too dark.

360 degree angle for the PIR sensor and a range of approx. 6 meters.

We recommend LED lighting for these sensors, as there is no warm-up time needed for a full brightness.

Buy online at:

www.matronics.eu/606631

Specifications

Angle	360 degree
Voltage	220-240VAC
Range	6m
Working temperature	-20 to 40 degree celcius
Light sensitivity	3-2000 Lux
Time delay	Min 10s (±3s) - Max 5min (±2min)
Installation height	~ 1,8 - 2,5m
Consumption	0,45W active - 0,1W inactive
Mounting hole	6,4 - 7,4 cm
Max current	5A
Max load	1200W



230V PIR motion sensor for mounting in the ceiling - 5A

SKU 606631

Dimensions: 61 x 60mm

Product pictures

