

Push Dimm transformer - 230VAC - 12VDC

A power supply with an integrated dimmer, so it can be controlled with maintained units.



The power supply has standard 230V input and 12V DC output. With the built in dimmer you avoid having to connect a separate dimmer unit. It can dim from 0% to 100%.

It can be controlled with push-button and 150W also can handle 0-10V signal, 10V PWM and resistor / potentiometer.

Push-button / potentiometer is not included.

Buy online at:

www.matronics.eu/503380



3000mA - 36W

SKU 503379
 Input voltage: 100-240VAC
 Power factor: >0.85
 Output voltage: 12VDC
 Consumption: 36W
 Current: 3A
 Temperature: - 30°C ~ 65°C
 Weight: 200
 Dimensions: 30 x 175 x 44mm



6.250mA, 75W

SKU 503380
 Input voltage: 100-240VAC
 Power factor: >0.99
 Output voltage: 12VDC
 Consumption: 75W
 Current: 6.2A
 Temperature: - 30°C ~ 65°C
 Weight: 500
 Weight: 500
 Dimensions: 30 x 293 x 43mm



12.500mA - 150W

SKU 503385
 Input voltage: 100-240VAC
 Power: >0.99
 Output voltage: 12VDC
 Current: 12.5A
 Consumption: 150W
 Weight: 580
 Dimensions: 36 x 270 x 55mm

Product pictures

