Staircase Timer, DIN, AC 23OV

A simple adjustable relay with a delay for turning the relay off, from ½ minute to 20 minutes. A built-in switch to turn the light on or off manually.



A simple adjustable timer with a delay for turning the relay off, from $\frac{1}{2}$ minute to 20 minutes.

A short pulse on the input will activate the relay for the set duration. After the time has passed the relay turns off again. By pulsing for 3 seconds you can force it on for 60 minutes. This can only be deactivated again with a 3 second pulse.

The built-in switch allows you to turn the light on or off manually or set it to auto and let the timer do it for you.

The timer has a low power consumption of only 1.9W.

There is only an english manual included.

matronics.11

Buy online at www.matronics.eu/612003

Specifications

Powersupply 240V AC Max current 16A

Max relay voltage 250VAC / 24VDC
Mounting DIN rail (EN60715)

Mechanical lifetime 1 x 10^7 Electrical lifetime 1 x 10^6 Output SPST

Product overview

Staircase Timer, DIN, AC 23OV



SKU 612003

Product pictures



